


GPS based Azimuth Adjustment tool to azimuth base station antennas in the field.

- Compatible to all Panel Antennas
- Easy to adapt onto an Antenna
- Compact size
- No cabling necessary

Type No.	86010157
GPS Sensor Specification	
Receiver Type	L1, C/A code, with carrier Phase smoothing
Channels	Two 12-channel, parallel tracking
SBAS Tracking	2-channel, parallel tracking
Used Geodetic System	WGS 84
Update Rate	10 Hz (10 measurement values per sec.)
Horizontal Accuracy	< 1.0 m 95% confidence (DGPS ¹⁾ < 2.5 m 95% confidence
Heading Accuracy	± 0.8°
Pitch/Roll Accuracy ²⁾	± 0.25°
Heave Accuracy ³⁾	30 cm
First start	max 12 min. (primary initialisation of almanac)
Cold Start	< 60 s (no almanac or RTC)
Warm Start	< 20 s typical (almanac or RTC)
Heading Fix	< 10 s typical (valid position)
Interface	W-LAN (802.11); RS 232 (optional)
Power Supply	LiPo-Battery (14.8 V, 2200 mAh)
Input Voltage	18 – 28 VDC
Power Consumption	5 W nominal; 36 W charging mode
Protection class	IP 54
Operating Temperature	-10 °C to +50 °C
Storage Temperature	-10 °C to +60 °C
Charing Temperature	0 °C to +45 °C
Certifications	FCC; CE
Dimensions (L x W x H)	580 (900 deployed) x 116 x 65 mm
Weight	3.1 kg



¹⁾ Depends on multipath environment, number of satellites in view; satellite geometry, ionospheric activity and use of SBAS.

²⁾ After calibration.

³⁾ Based on a 40 second time constant.

Tablet Specification	
Model	ICECARE
Display	
LCD Size	7" TFT LCD
Brightness (cd/m ²)	500 cd/m ²
Max Resolution	1024 (H) x 552 (V)
Viewing Angle	60/70/70/70 Deg.
Touch Screen	Projective capacitive type
Operating System	Android 4.x
Memory	4 GB eMMC Flash + 512 MB SDRAM
Storage	SD Slot (max. 32 GB)
Communication	
W-LAN	802.11 b/g/n
Bluetooth	Bluetooth 2.1+EDR
Modem	HSUPA / GPRS / GSM
RFID	HF RFID; ISO 14443A; ISO 14443B; ISO 15693; NFC
Data Collection	
Bacode	1D laser / 2D imager scan engine
Camera (Back)	5 megapixels CMOS camera
Camera (Front)	2 megapixels CMOS camera
I/O Interface	
Audio	1 x 1.5 W speaker; 1 x Digital Mic
Expansion	2 x USB 2.0; 1 x DC Jack
Power	Dual 11.1 V, 1880 mAh, Li-ion battery
Environment	
Operating Temperatur	-10 °C to +40 °C
Storage Temperatur	-10 °C to +60 °C
Drop Survival	1.2 m
Protection class	IP 64
Certification	CE / FCC
Dimensions (L x W x H)	248 x 153 x 36 mm
Weight	0.95 kg
Scope of Supply	GPS Azimuth Adjustment Tool; Tablet PC; Adapterplates; Charging Device; Storage and carrying bag, SD-Card (32GB); Cables
Shipment Dimension (L x W x H)	700 x 350 x 300 mm
Shipment Weight	5.2 kg



Please note:

The installation team must be properly qualified and also be familiar with the relevant national safety regulations! Non-observance of these instructions may damage or destroy the devices. Death or severe injuries may occur! The details given in the product documentation must be carefully followed during the installation and operation of the GPS Azimuth Adjustment Tool (read the product documentation thoroughly before connecting the GPS Azimuth Adjustment Tool to the power supply).

936.A3127 Subject to alteration.

FCC – Statements

FCC § 15.19

This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC § 15.105

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Canada CNR-Gen Section 7.1.3

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

ICES-003

This Class B digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe B est conforme à la norme NMB-003 du Canada.

FCC § 15.21 (Warning Statement)

[Any] changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Compliance Information Statement (Declaration of Conformity Procedure)

Responsible Party: Kathrein Inc., Scala Division

Address: PO Box 4580, Medford Oregon . 97501

Telephone: (+01)541 779 6500

Type of Equipment:



Trade name: GPS Azimuth Adjustment Tool

Model number: 86010157